

HOOK-UP SHEET CAT# MOD-6 RF / VIDEO MODULATOR

Wire Color codes

There are two versions of this modulator. They look and function the same, but the input wires have different color codes. The easiest way to make the audio, video and power connections is to cut off the mini-DIN plug and splice to the wires in the cable. The color codes are as follows:

Version #1— 3 wires

Shield – Ground
Clear wire – Video in
Green – Vcc 5-6 Vdc
Orange – Audio in

Version # 2 – 4 wires

Black wire – Ground
Yellow wire – Video in
Pink (red) wire – Vcc 5-6 Vdc
White – Audio in

